

Pure Sine Wave 2000 Watt Inverter

With Bluetooth Remote Control Function

Powers 240V appliances from a 12V automotive battery/240V AC power source – HIP2000WL

Features:

- Removable 2.4 inch Bluetooth colour LCD display with touch screen functionality for switching main unit on/off and displays inverter input voltage, amperage, output AC wattage and also low voltage warning
- Dual 240VAC outlet
- RCD switch for short circuit protection, instantaneous output cut-off for power leakage protection and to turn 240VAC output on or off
- Automatic AC transfer switch when 240VAC input is detected
- Low voltage warning at 11.5V with flashing voltage reading on the voltage gauge
- Shuts down output at 11V along with visible warning on LCD screen
- Over/under voltage, output short circuit, over temperature protection
- 1 year warranty



Specifications:

Continuous Output Power	2000W
Minimum Input Voltage	11V
Output Voltage	240VAC
Output Frequency	50Hz
Output Waveform	Pure Sine Wave
AC Transfer Switch	Yes
RCD Switch protection	Yes, 10A240VAC, t≤0.1s
LCD display functions	Displays output power, input voltage, input current and also has an on/off button for switching unit on/off
LCD screen extra cable length	1.7m extension cable for LCD display unit 12V power supply
Output Overload protection(Manual restart)	2100W
Protection systems (Output)	Over/under-voltage protection, Overheating protection, Overload protection, Short circuit protection
External fuse specification	150A